

SYSTEMS AND CONTROL / VOICE ALARM EN 54 / COMPACT

## **SMART-PA8080**

POWER AMPLIFIER 8X 80 W







ESPECIALLY RECOMMENDED IN:



All sectors

## **DESCRIPTION**

The SMART-PA amplifiers are designed for perfect integration into the SMART system solutions and are certified according to the EN 54-16 standard for security installations. SMART-PA is a family of class D power amplifiers isolated by transformer. They allow the use of individual channel power or bridge mode, bridging two channels to achieve double the output power. These amplifiers are powered through a 48 V DC input. This power is



+ Info:

https://fonestar.com/SMART-PA8080

**FONESTAR** 

Poligono Trascueto. 39600 Revilla de Camargo. Cantabria (España)



supplied and controlled through the SMART-PSM power supply manager, which connects both to power supplies and batteries. This ensures maximum availability and durability in a voice evacuation system.

## **TECHNICAL CHARACTERISTICS**

FEATURES	Class D power amplifier. Isolated output with transformer. The output channels can be used in bridge mode. 100 V or 50 V speaker line output. Front panel indicators for Power, Active and Fault. The SMART-PA series is combined with the SMART-PSM48/E Power Manager (charger and back-up power supply).
POWER	8x 80 W Bridge mode: 1x 160 W + 6x 80 W 2x 160 W + 4x 80 W 3x 160 W + 2x 80 W 4x 160 W
RESPONSE	75 Hz – 22 kHz (–6 dB)
INPUTS	8 Audio input controlled by the ABT audio manager. RJ-45 connector.
OUTPUTS	8 x 50/100 V speaker line for connection to the SMART-CU control unit, Euroblock
SIGNAL/NOISE RELATION	> 85 dB (@1 kHz 22 Hz - 22 kHz)
CROSSTALK	< -70 dB (between channels 50 Hz - 20 kHz rated load)
POWER THD	< 10%
POWER SUPPLY	48 V CC provided by SMART-PSM power supply manager, threaded terminals Tension range: 42 - 57 V CC Fuses (internal): 6× 7'5 AF-H Consumption: 0'2 A (standby), 0'7 A (active) and 20 A (maximum rated current) Nominal overall efficiency CC maximum output power at 1 kHz: 80%
DIMENSIONS	482 x 85 × 445 mm depth, 2U 19' rack
WEIGHT	15 kg



+ Info:

https://fonestar.com/SMART-PA8080